

ADDENDUM – SUPER SNAPSHOT v 5.2

Last minute alterations to the product make this brief update necessary. The following is a listing of all additions and omissions pertaining to this version (5.2).

ADDITIONS

INFINITE LIVES GENERATOR: This utility (my favourite) is not referred to in the manual. It is straight forward and requires only a little explanation. The purpose of this addition is to make game playing easier by giving you infinite lives.

To use, load your game in like normal and then interrupt using *SUPER SNAPSHOT*. Choose the *GAME MASTER MENU* and select *INFINITE LIVES*. You will be asked to enter the number of lives that you have left and then resume the game. Lose another life and then go back to the *INFINITE LIVES* module. Again enter the number of lives left. At this point *SUPER SNAPSHOT* should be able to fix the game for you. It may ask you to go back and lose yet another life but it is unlikely. When *SUPER SNAPSHOT* does determine the necessary change it will display "INSTALLED". It will also give you the location (in HEX) that was modified so that if you wish to play the game some other time, you can install the infinite lives yourself. Just go to the Monitor and type D (location given). You will see a DEC command. Type AD over the CE and hit RETURN. Exit the Monitor and the change has been made. **NOTE** - You must reset your computer between each different game. A table is stored on the RAM each time *INFINITE LIVES* is used. If the computer is not reset (or clean) when a new game is started, then there is garbage on the RAM. If this happens *SUPER SNAPSHOT* will let you know by displaying "NOTHING" and will tell you to go back to *GAME MASTER* and try *INFINITE LIVES* again. It just means an extra step.

SNAPTERM: Both *Punter* and *Ansi* support have been included on the ROM. The *Ansi* support is installed automatically. This means that you can log on to BBS's that use *Ansi* control codes and you will not have a corrupted screen. *Punter* support appears when you choose the *Download or Upload* option. You will be asked *XMODEM or PUNTER c1* and you just make your choice.

DISK COPIERS: All disk copiers are now cartridge resident and work as described in the manual. **1581 USERS NOTE:** When using the single 1581 copier, if your source disk is not write protected, you will be informed with the prompt, "CONTINUE Y/N?". If you wish to flip the write protect tab, eject the disk at this point and do so; then press Y to continue. We have found that some 1581's act erratically when N is pressed at this prompt. If you do press "N", then cycle through the (M)ode once at the Main Menu.

NEW COMMANDS

- 1) From Basic: *DCOPY* - takes you directly to our disk copiers; *FCOPY* - takes you to our file copier.
- 2) *SNAPTERM* - several new features are available in *SNAPTERM*. They are described in the Help Screen (*COMMODORE H*)... and yes, the carriage returns *WITH* linefeeds is there!

OMISSIONS

Our *SUPER DISK SNAPSHOT* (Nibbler) was completed on time but unfortunately it is still not copying 100% reliably. Rather than release it in this condition, we have opted to hold it back and work on it further. When completed, it will be available on our BBS for downloading.

NO room on the disk for a *Slideshow Creator* demo. *SLIDESHOW CREATOR PLUS* is still scheduled for release later this year. We accept BO's for this one. V5 does *not* support the older version of this program - sorry.

ADDITIONAL NOTES

SUPERTERM, SECTION 4.5, appears on page 25 of our manual and *ROM UPDATES*, SECTION 15.0, on page 42.

SPRITES: Printed only in medium & large sizes; toggle space bar to see exactly what you have captured.

NX-1000C RAINBOW : Some older models do not properly emulate their Epson counterparts. Contact *STAR MICRONICS* for a printer ROM update. Colour dumps only in medium & large sizes.

PLEASE NOTE: If you reset your computer by turning it off and then on, please hold down the *LEFT ARROW KEY* as you do so. This will reset the cartridge RAM. Otherwise, the function key definitions may be corrupted.

RMA NUMBER: Please contact either *Software Support International or Marhview Software Ltd.* to obtain an RMA number before returning product. This number **MUST** be clearly stated on the outside of the package. Product returned without an RMA will **NOT** be accepted!

OOOPS!: *BASIC PLUS: PRINTON* diverts output from the screen to the printer. The *OLD* command is used *WITHOUT* the £.

SUPER SNAPSHOT v5.2 ADDENDUM

HELLO

Last minute alterations to the product make this brief update necessary. The following is a listing of all additions and omissions pertaining to this version (5.2).

ADDITIONS

INFINITE LIVES GENERATOR: This utility (my favorite) is not referred to in the manual. It is straight forward and requires only a little explanation. The purpose of this addition is to make game playing easier by giving you infinite lives.

To use, load your game in like normal and then interrupt using SUPER SNAPSHOT. Choose the GAME MASTER MENU and select INFINITE LIVES. You will be asked to enter the number of lives that you have left and then resume the game. Lose another life and then go back to the INFINITE LIVES module. Again enter the number of lives left. At this point SUPER SNAPSHOT should be able to fix the game for you. It may ask you to go back and lose yet another life but it is unlikely. When SUPER SNAPSHOT does determine the necessary change it will display "INSTALLED". It will also give you the location (in HEX) that was modified so that if you wish to play the game some other time, you can install the infinite lives yourself. Just go to the Monitor and type D (location given). You will see a DEC command. Type AD over the CE and hit RETURN. Exit the Monitor and the change has been made. NOTE - you must reset your computer between each different game. A table is stored on the RAM each time INFINITE LIVES is used. If the computer is not reset (or clean) when a new game is started, then there is garbage on the RAM. If this happens SUPER SNAPSHOT will let you know by displaying "NOTHING" and will tell you to go back to GAME MASTER and try INFINITE LIVES

again. It just means an extra step.

SNAPTERM: Both Punter and Ansi support have been included on the ROM. The Ansi support is installed automatically. This means that you can log on to BBS's that use Ansi control codes and you will not have a corrupted screen. Punter support appears when you choose the download or upload option. You will be asked XMODEM or PUNTER cl and you just make your choice.

DISK COPIER: All disk copiers are now cartridge resident and work as described in the manual. 1581 USERS NOTE: When using the single 1581 copier, if your source disk is not write protected, you will be informed with the prompt, "CONTINUE Y/N?". If you wish to flip the write protect tab, eject the disk at this point and do so; then press Y to continue. We have found that some 1581's act erratically when N is pressed at this prompt. If you do press "N", then cycle through the (M)ode once at the Main Menu.

NEW COMMANDS

- 1) From Basic: DCOPY - takes you directly to our disk copiers; FCOPY - takes you to our file copier.
- 2) SNAPTERM - several new features are available in SNAPTERM. They are described in the Help Screen (COMMODORE H) - and yes, the carriage returns WITH linefeeds feature is there!

OMISSIONS

Our SUPER DISK SNAPSHOT (Nibbler) was completed on time but unfortunately it is still not copying 100% reliably. Rather than release it in this condition, we have opted to hold it back and work on it further.

When completed, it will be available on our BBS for downloading.

No room on the disk for SlideShow Creator demo. SLIDESHOW CREATOR PLUS is still scheduled for release later this year. We accept BO's for this one. V5 does not support the older version of this program - sorry.

ADDITIONAL NOTES

SUPERTERM, SECTION 4.5, appears on page 25 of our manual and ROM UPDATES, SECTION 15.0, on page 42.

SPRITES: Printed only in medium and large sizes; toggle space bar to see exactly what you have captured.

NX-1000C RAINBOW: Some older models do not properly emulate their Epson counterparts. Contact STAR MICRONICS for a printer ROM update. Colour dumps only in medium and large sizes.

Please note if you reset your computer by turning it off and then on, please hold down the LEFT ARROW KEY as you do so. This will reset the cartridge RAM. Otherwise, the function key definitions may be corrupted.

RMA NUMBER: Please contact either Software Support International or Marshview Software Ltd. to obtain an RMA number before returning product. This number MUST be clearly stated on the outside of the package. Product returned without an RMA will NOT be accepted!

OOPS!: BASIC PLUS; PRINTON diverts output from the screen to the printer. The OLD commands is used WITHOUT the £.